



6W 2-PIN GX23 Base LED Commercial Bulbs



- 13W GX23 Base Replacement Using Only 6W
- Installs in seconds
- CFL bulbs in downlights, sconces and other fixtures with 2-PIN GX23.

These energy-saving LED lamps are quick, easy and safe to install into existing CFL fixtures without any extra effort or re-wiring.

- Ballast compatible (**120V-277V**)
- No lumens lost over life of product
- Suitable for use with wall-mounted and ceiling fixtures
- 5-year warranty
- LDL Approved (Lighting Design Lab) (website: www.lightingdesignlab.com)

This PL lamp has an adjustable base that can be rotated to **270°** to fit any socket configuration. After it is installed, easily rotate the lamp to adjust the maximum light output.



Plug & Play or Bypass
PL Direct Replacement

UPC	Description	Lumens	Life (Hours)	CFL PLC Replacement	Beam Angle	M.O.L.	CCT	CRI
40168	6W LED 2-PIN GX23 Base 120V-277V	520	50,000	13W in GX23 Base	180°	5.79"	3500K	80

Certifications LM-80, TM-21, IES, LDL.
Pending Certifications: LM-79

*Use in high wattage ballast may effect life expectancy.

